

OTT150-CFF03

15 inch Flat Screen Touch Monitor

Projected Capacitive Touch screens 10 points touch Water proof&Vandal proof



OTT150-CFF03	Projected capacitive (PCAP) Touch Screen	VGA/DVI/HDMI	Metal Front Frame
--------------	--	--------------	-------------------

OASIS TOUCH TECHNOLOGIES

www.oasistouch.co.in

sales@oasistouch.co.in | sales.oasistouch@hotmail.com, Ph.8600888766

OTT150-CFF03

15 inch Flat Screen Touch Monitor

Projected Capacitive Touch screens 10 points touch Water proof&Vandal proof

Safety Instructions

1. Read these safety instructions carefully.
2. Disconnect this equipment from any AC outlet before cleaning. Use a damp cloth. Do not use liquid or spray detergents for cleaning.
3. For plug-in equipment, the power outlet socket must be located near the equipment and must be easily accessible.
4. Keep this equipment away from humidity.
5. Put this equipment on a reliable surface during installation. Dropping it or letting it fall may cause damage.
6. The openings on the enclosure are for air convection. Protect the equipment from overheating. **DO NOT COVER THE OPENINGS.**
7. Make sure the voltage of the power source is correct before connecting the equipment to the power outlet.
8. Position the power cord so that people cannot step on it. Do not place anything over the power cord.
9. All cautions and warnings on the equipment should be noted.
10. If the equipment is not used for a long time, disconnect it from the power source to avoid damage by transient over voltage.
11. Never pour any liquid into an opening. This may cause fire or electrical shock.
12. Never open the equipment. For safety reasons, the equipment should be opened only by qualified service personnel.
13. If one of the following situations arises, get the equipment checked by service personnel:
 - A) The power cord or plug is damaged.
 - B) Liquid has penetrated into the equipment.
 - C) The equipment has been exposed to moisture.
 - D) The equipment does not work well, or you cannot get it to work according to the user's Manual.
 - E) The equipment has been dropped and damaged.
 - F) The equipment has obvious signs of breakage.
14. **DO NOT LEAVE THIS EQUIPMENT IN AN UNCONTROLLED ENVIRONMENT WHERE THE STORAGE TEMPERATURE IS BELOW -10°C OR ABOVE 50°C. THIS MAY DAMAGE THE EQUIPMENT.**

OASIS TOUCH TECHNOLOGIES

www.oasistouch.co.in

sales@oasistouch.co.in | sales.oasistouch@hotmail.com, Ph.8600888766

OTT150-CFF03

15 inch Flat Screen Touch Monitor

Projected Capacitive Touch screens 10 points touch Water proof&Vandal proof

General

Model	OTT150-CFF03
Series	Water-proof and Open frame
LCD Type	15" Active matrix TFT-LCD
Video Input	VGA ,DVI and HDMI, RS232
OSD controls	Allow on-screen adjustments of Brightness, Contrast Ratio, Auto-adjust, Phase, Clock, H/V Location, Languages, Function, Reset
Power Supply	Input (line) voltage: 100-240 VAC, 50-60 Hz Output voltage/current: 12 volts at 4 amps max
Mount Interface	1)VESA 75mm and 100mm 2)Mount bracket, horizontal or vertical
LCD Specification	Active Area(mm) 304.128(H)×228.096(V)
Resolution	1024×768@75Hz
Dot Pitch(mm)	0.297×0.297
Nominal Input Voltage VDD	+3.3V(Typ)
Viewing angle (v/h)	89°/89°
Contrast	1500:1
Luminance(cd/m2)	300
Response Time(Rising)	2ms/6ms
Support Color	16.2M
Backlight MTBF(hrs)	50000
Touchscreen Specification	Projected Capacitive touch screen
Multi touch	10 Points Touch
Touch Life Cycle	10 millions

OASIS TOUCH TECHNOLOGIES

www.oasistouch.co.in

sales@oasistouch.co.in | sales.oasistouch@hotmail.com, Ph.8600888766

OTT150-CFF03

15 inch Flat Screen Touch Monitor

Projected Capacitive Touch screens 10 points touch Water proof&Vandal proof

Touch Response time	8ms
Touch System Interface	USB interface
Power consumption	+5V@80mA
External AC Power Adapter Output	DC 12V /4A
Input	100-240 VAC, 50-60 Hz
MTBF	50000 hr at 25°C
Environment Operating Temp.	0~50°C
Storage Temp.	-20~60°C
Operating RH:	20%~80%
Storage RH:	10%~90%

1.2 Components


USB Cable 180cm*1 Pcs,
VGA Cable 180cm*1 Pcs,
Power Cord with Switching Adapter *1 Pcs,
Bracket*2 Pcs



1.3 OSD Control

1.3.1 OSD buttons

1.3.2 Adjusting



OASIS TOUCH TECHNOLOGIES

www.oasistouch.co.in

sales@oasistouch.co.in | sales.oasistouch@hotmail.com, Ph.8600888766

OTT150-CFF03

15 inch Flat Screen Touch Monitor

Projected Capacitive Touch screens 10 points touch Water proof&Vandal proof

1.3.2 Adjusting with OSD control

Five different keys are well-defined for operation. They are labeled on the keypad.

A) **[Power]** Key is designated for Power On/Off

B) **[Menu]** Key is designated for Menu/Enter function depending on the selected item. Pressing [Menu] can invoke OSD

Menu. After that, [Menu] is also an entry key.

C) **[+]** key is designated for selection function in up direction in OSD menu and also to increase the value on selected

Function, directly use + Key is to increase brightness.

D) **[-]** key is designated for selection function in down direction in OSD menu and also to decrease the value on selected

Function, directly use - Key is to decrease brightness.

E) **[AUTO]** key is designated for invoking AUTO ADJUST function at any time once is pressed for H-position, V-position,

Pixel Clock and Phase for an optimal image.

1.4 Setup the driver

1. Plug and play USB port under win 7 win 8 win 10. For Android and Linux need using driver pls contact the sales for support.

1.5 Warranty

1 Year Free Warranty for Monitor and all components.

OASIS TOUCH TECHNOLOGIES

www.oasistouch.co.in


sales@oasistouch.co.in | sales.oasistouch@hotmail.com, Ph.8600888766

OTT150-CFF03

15 inch Flat Screen Touch Monitor

Projected Capacitive Touch screens 10 points touch Water proof&Vandal proof

1.6 Mechanical Drawing



OASIS TOUCH TECHNOLOGIES

www.oasistouch.co.in

sales@oasistouch.co.in | sales.oasistouch@hotmail.com, Ph.8600888766